

## Water injection/extraction car seat cleaner



MANAGEMENT WITH PLC



ELECTRONIC COIN ACCEPTOR



LEFT OR RIGHT PIPE OUTLET



CONNECTION TO MAINS WATER



AUTOMATIC DRAIN



LOCKABLE COIN BOX



REMOTE MANAGEMENT

### Standard features and equipment:

- ✓ Structure in Aisi 304 stainless steel
- ✓ ABS cover
- ✓ Full-length stainless steel door hinge
- ✓ Vandal-proof 3-point lock
- ✓ 5m hose with injection/extraction nozzle
- ✓ Right or left pipe outlet
- ✓ Mains water connection
- ✓ Automatic drain with safety floater
- ✓ Electronic management with PLC
- ✓ Electronic coin acceptor
- ✓ Lockable coin box
- ✓ LED operation lights
- ✓ Back-lit LED steel buttons
- ✓ Turbine 230 - 400 V


### Optional (on request):

- ✓ Coin acceptor protection
- ✓ LED lighting kit
- ✓ Card reader (cashless)
- ✓ Remote management
- ✓ Boom
- ✓ Stainless steel cover
- ✓ Safety bars
- ✓ Antifreeze kit
- ✓ Turbine 3kW
- ✓ Up to 2 optional kits, with a maximum of 1 liquid kit


- **AR** compressed air kit (requires external air)
- **BA** antibacterial Kit (requires external air)
- **SA** perfume/sanitizing Kit
- **NG** tire blackening kit
- **VE** glass cleaner kit
- **LC** dashboard polish kit



## Water injection/extraction car seat cleaner



Vandal-proof 3-point lock (standard)



Lockable coin box (standard)



PLC (standard)



Optional service kit dispensers




Full-length stainless steel door hinge (standard)



Detergent dosing pump (standard)



LED lighting kit (on request)



Antifreeze kit (on request)



Boom (on request)



### Remote management

The machine, connected to the internet, sends data to a cloud server where dedicated software processes it and makes it available to the operator, who can monitor in real time the machine's operating status, income, and a series of alerts.

In the same way, the operator can send commands to the machine to change the cost and duration of selections, start a specific service, and reset or shut down the machine.

### Model:

Code	Model	Volt	Power	m <sup>3</sup>	Det. tank	Water	Pump	Dirty Tank	Weight
CW0323000	Starline 230	230	2,4 kW	320	10L	2>5 bar	2>6 Lt/h	50 L	110 Kg
CW0340000	Starline 400	400+N	2,4 kW	320	10L	2>5 bar	2>6 Lt/h	50 L	110 Kg

### Optional on request:

Coin acceptor protection cod. <b>PG</b>
LED lighting kit cod. <b>LE</b>
Stainless steel cover cod. <b>CIS</b>
Boom cod. <b>BR</b>
Safety bars cod. <b>BSS</b>
Card reader (cashless) cod. <b>PK</b>
Remote management cod. <b>CLOUD</b>
Turbine 3kW - 400V cod. <b>T3KW</b>

Compressed air kit* cod. <b>AR</b>
Perfume/Sanitizing kit cod. <b>SA</b>
Antibacterial kit* cod. <b>BA</b>
Dashboard polish kit cod. <b>LC</b>
Tire blackening kit cod. <b>NG</b>
Glass cleaner kit cod. <b>VE</b>
antifreeze kit cod. <b>AN</b>

\* Requires external air

